

## T-Box for Suspended Ceiling Grids

**NEW!**

Can be positioned on the ceiling grid at the cross of the T-rails or on the straight away. For use on premium/reveal edge ceiling tiles, the box height adjusts by removing the tabs with pliers.

### FEATURES AND BENEFITS

- 28.0 cu. inch box, available in two styles
- Meets 2017 NEC, section 314.27 for fan and fixture boxes
- Uses include fans, fixtures, smoke and carbon monoxide detectors, security cameras, exit signs, and emergency lighting





F428SC





FB428SC

| CATALOG NUMBER | UPC/DCI/NAED MFG #018997 | DESCRIPTION                                       | UNIT PKG | STD PKG | DIM A | DIM B | DIM C |
|----------------|--------------------------|---------------------------------------------------|----------|---------|-------|-------|-------|
| F428SC         | 06910                    | Plastic hanger, For fixtures (only), up to 50 lbs | 1        | 10      | 4.355 | 3.125 | -     |
| FB428SC        | 06911                    | Metal hanger, For fans/ fixtures up to 70 lbs     | 1        | 10      | 4.355 | 3.250 | 3.875 |



F428SC



FB428SC

### KIT INCLUDES...

**F428SC:** 12ft support wire coil, installed NM cable connector, grid cover

**FB428SC:** Wire Grabber™ with braided drop wire support kit, installed NM cable connector, (2) #10-32-32 x 4" screws, grid cover



E170558

## INSTALLATION INSTRUCTIONS

### 1 Locate position of item to install.

A = straight on T-bar rail  
B = intersection of T-bar rail (cross)



### 2 Cut out around ceiling tile.

A = for straight  
B = for cross



### 3 Drop box onto grid from overhead.

Remove tabs as necessary to adjust ceiling tile height.



Attach drop wire to structural member. Install NM cable through installed NM cable connector. Reinstall ceiling tiles.

### 4 Install fan, fixture or other item per manufacturer's instructions.

#### FOR FANS/FIXTURES

Install bracket with supplied screws.

FB428SC on straight grid

Supplied screws

**FOR FIXTURES** Use screws supplied by fixture manufacturer.

F428SC on cross grid