

Main

|                              |                                              |
|------------------------------|----------------------------------------------|
| AC Magnetic Trip Setting     | 1700A Fixed Trip (900A Hold)                 |
| Ampere Rating                | 100A                                         |
| Approvals                    | UL Listed - CSA Certified                    |
| Circuit Breaker Type         | Extra High Interrupting                      |
| For Use With                 | I-Line Panelboards and Switchboards          |
| Frame Type                   | F-Frame                                      |
| HACR Rated                   | Yes                                          |
| Marketing Trade Name         | Square D                                     |
| Mounting Type                | Plug-On                                      |
| Number of Poles              | 3-Pole                                       |
| Phase Connection             | ABC                                          |
| Short Circuit Current Rating | 65000AIR@480VAC                              |
| Type                         | FC                                           |
| Voltage Rating               | 480VAC                                       |
| Weight                       | 5 Pounds                                     |
| Width                        | 4.50 Inches                                  |
| Wire Size                    | (1)#12 to #1 AWG(Al) or (1)#14 to #3 AWG(Cu) |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.