

# 4" Square Double Gang Device Rings



## Features

- Ideal for exposed work applications, providing an easy method for the installation of electrical devices
- Can be used on any 4" square box

## Applications


- 4" double gang device rings are used with 4" square boxes to mount switches, receptacles and devices
- Angled slots on the covers compensate for up to 12° of box misalignment on upright framing members
- Four slots for mounting vertically or horizontally

## Standard Material


- Galvanized steel




**R2240**




**R2241**




**R2242**




**R2243**



**R2244**



**R2245**



**R2246**



**R2247**



**R2248**

| Catalog Number | UPC   | Description   | Depth  | Cubic Inches | Ship Case | Weight/Case |
|----------------|-------|---------------|--------|--------------|-----------|-------------|
| <b>R2240</b>   | 01542 | Flat          | Flat   | ---          | 200       | 21          |
| <b>R2241</b>   | 86731 | Raised 1/4"   | 1/4"   | 2.3          | 200       | 24          |
| <b>R2242</b>   | 86732 | Raised 1/2"   | 1/2"   | 5.4          | 100       | 22          |
| <b>R2243</b>   | 86733 | Raised 5/8"   | 5/8"   | 7            | 100       | 36          |
| <b>R2244</b>   | 86734 | Raised 3/4"   | 3/4"   | 8.5          | 100       | 38          |
| <b>R2245</b>   | 86735 | Raised 1"     | 1"     | 11.6         | 50        | 40          |
| <b>R2246</b>   | 86736 | Raised 1-1/4" | 1-1/4" | 14.7         | 50        | 21          |
| <b>R2247</b>   | 01021 | Raised 1-1/2" | 1-1/2" | 15.5         | 50        | 22          |
| <b>R2248</b>   | 01022 | Raised 2"     | 2"     | 20.7         | 50        | 23          |